

HF6 1.8KW LADEGERÄT



- Hochfrequenzladegerät mit einem Wirkungsgrad > 90%
- 8 Ladeprofile
- Verschiedene Ladekennlinien für entsprechende Einsätze wählbar (Sonderkennlinien programmierbar)
- Für Nass,-AGM -und Gelbatterien einsetzbar
- Leichte und kleine Geräte, einfache Wandmontage möglich
- Wechselspannung 230VAC ± 10% 50/60 Hz
- Anzeigen auf dem LCD - Display:
Ladekennlinie, Ladestrom (A), Batteriespannung (U), Ladezeit (h), Geladene Kapazität (Ah), Signalisierung bei Fehlfunktion, Anzeige des Fehlercodes

Modell	Ah Batterie		Netz	Art. Nr.
	7 ÷ 8 h	10 ÷ 12 h		
24V / 60A	360 ÷ 420	480 ÷ 600	230 Vac	ZB.PRLHF62460
24V / 70A	420 ÷ 490	560 ÷ 700	230 Vac	ZB.PRLHF62470
36V / 40A	240 ÷ 280	320 ÷ 400	230 Vac	ZB.PRLHF63640
36V / 45A	270 ÷ 315	360 ÷ 450	230 Vac	ZB.PRLHF63645
48V / 30A	180 ÷ 210	240 ÷ 300	230 Vac	ZB.PRLHF64830
48V / 35A	210 ÷ 245	280 ÷ 350	230 Vac	ZB.PRLHF64835
72V / 22A	132 ÷ 154	176 ÷ 220	230 Vac	ZB.PRLHF67222
80V / 20A	120 ÷ 140	160 ÷ 200	230 Vac	ZB.PRLHF68020



HF6 1.8kW BATTERY CHARGER



- High Frequency battery charger with efficiency > 90%
- 8 Charge profiles
- Various charging characteristics selectable for corresponding applications (special characteristics programmable)
- Can be used for Wet, AGM, and Gel batteries
- Lightweight and small devices, easy wall mounting possible
- AC voltage 230VAC $\pm 10\%$ 50/60 Hz
- Indications on LCD display:
Charging curve, charging current (A), battery voltage (U), charging time (h), charged capacity (Ah), signaling in case of malfunction, display of the error code

Model	Ah Battery		Mains	Art. No.
	7 ÷ 8 h	10 ÷ 12 h		
24V / 60A	360 ÷ 420	480 ÷ 600	230 Vac	ZB.PRLHF62460
24V / 70A	420 ÷ 490	560 ÷ 700	230 Vac	ZB.PRLHF62470
36V / 40A	240 ÷ 280	320 ÷ 400	230 Vac	ZB.PRLHF63640
36V / 45A	270 ÷ 315	360 ÷ 450	230 Vac	ZB.PRLHF63645
48V / 30A	180 ÷ 210	240 ÷ 300	230 Vac	ZB.PRLHF64830
48V / 35A	210 ÷ 245	280 ÷ 350	230 Vac	ZB.PRLHF64835
72V / 22A	132 ÷ 154	176 ÷ 220	230 Vac	ZB.PRLHF67222
80V / 20A	120 ÷ 140	160 ÷ 200	230 Vac	ZB.PRLHF68020

